## GAZELLE G9406 Mini Sound Level Meter

The G9406 is widely used in noise detection, quality control, health and safety, and environmental noises. The compact design of G906 makes it ideal for mobile measurements of sound.

Noise generated in various environments, at the workplace, at machine controls, on the construction site, at events can be easily and comfortably measured and displayed. The display gives clear results of the measurements made by the sound level meter. A backlight is also integrated into the display. This noise meter is a professional instrument for outdoors and indoors use with a high measuring accuracy of  $\pm$  1.5 dB.



- MAX/MIN modes
- Auto power off (cancelable)
- Data hold, LCD backlight
- Simulated analog bar
- A (ear)/C (machine) weighting modes
- Manual/auto range selectable
- Fast/slow response rate (fast: 125ms, slow: 1s)
- Powered by batteries or external power source







Functions	Range	Accuracy
Noise (A Weighting)	30~130dB (0.1dB Res)	±1.5dB
Sampling Rate	FAST	125ms
	SLOW	1000ms
MAX/MIN		MAX/MIN
Data Hold		HOLD
LCD Backlight		Yes
Battery		AAA 1.5V*3 batteries
Working Environment	Temperature	0~40°C
	Humidity	≤80%RH
Storage Environment	Temperature	-20~60°C
	Humidity	≤75%RH

## **Standard Accessories**

- Operating Manual
- 1.5V AAA 3pcs



